



# EMPEROR V2

JHS PEDALS

*True analog bucket brigade Chorus and Vibrato with tap tempo waveform selection and more.  
Classic modulation with modern amenities.*

## Controls

**Volume** - Controls output volume.

**EQ** - For the V2, the EQ control is an active tilt EQ. Noon is flat. Turning to the left boosts highs and cuts lows, while turning to the right boosts lows and cuts highs

**Speed** - Controls time/speed of the modulation.

**Depth** - Controls how deep/wet the modulation is perceived.

**Chorus/Vibrato Toggle** - Lets you choose between Chorus and Vibrato

**Waveform Toggle** - Choose between Sine, Square, and Triangle waveforms.

## Jacks

**INPUT** - 1/4" jack on the top right receives your instrument's signal.

**OUTPUT** - 1/4" jack on the top left sends the signal out of the pedal to an amplifier or pedal chain. You can use an optional TRS splitter cable to send your signal to two amps for true stereo modulation.

**TAP/EXP** - 1/4" jack on the right side of the pedal. In Expression Mode, connect any TRS expression pedal to control the pedal's speed. The speed parameters are preset for realistic rotary speaker sound. In Tap Mode you can set the speed using an external tap tempo pedal. Choose which one you want by the switch on the left side of the pedal.

## Switches

**BYPASS** - Left footswitch turns the pedal on and off.

**TAP TEMPO** - Right footswitch taps in the speed of the modulation.

**TAP/EXP** - Switch on the left side of the pedal. Choose between tap or expression mode for the TAP/EXP jack

**INTERNAL BUFFER SWITCH** - Switch lets you choose between true bypass and buffered bypass by engaging or disengaging the buffer.

---

**POWER** - Uses 9V DC Negative Center. Do not use more than 9V DC. Your warranty will be voided. 100mA max consumption.